Field Receiver



PART NUMBER: **2517**

FEATURES

Receives wireless signals from CurAlert transmitters

Communicates alarm and reset information to CurAlert PC software

Automatic fault detection and reporting to CurAlert PC software

Easy to program

Low cost

TECHNICAL SPECIFICATIONS

Operating voltage 9 to 13.8Vdc
Stand by current consumption < 20mA
Maximum of 254 field receivers per system
Hard wired communications protocol RS485 over CAT5E
RF operating frequency 433Mhz
RF sensitivity adjustment
Green LED indication of RS485 activity
Red LED indication of RF activity
Dimensions 165 X 85 X 55
Weight 300 grams
Grey durable ABS plastic enclosure
10m RF coverage when used with other CurAlert products

ACCESSORIES

2514 CurAlert Software, **2522** Field Receiver Programmer, **2523** Bidirectional Data Convertor, **2515** Infant Transmitter, **2573** Wristband Duress Transmitter, **2558** Wireless Call Button, **2559** Wireless Reset Button, **2401** 1A Power Supply, **2402** 2.5A Power Supply, **2403** 5A Power Supply

cura1.com

cura¹ products are designed to augment well designed care programs and practices, cura1 does not claim that any of its products are suitable as a substitute, or as a total solution for individuals that require care and constant supervision, and are at risk.