CurAlert Door Monitor



PART NUMBER: **2521**

FEATURES

Automatically detects Infant Transmitters and alerts carers

Easy installation and simple operation

Easily expandable and configurable

Low maintenance

Adjustable detection range

Fully wireless - no cabling required

Flashing LED light and adjustable audible alarm

Can be connected to a nurse call system

Caregiver key reset option

Caregiver Reset Transmitter option

TECHNICAL SPECIFICATIONS

9-13.8 Vdc operation (stand by current consumption <100mA)
Red LED and adjustable audible sounder alarm indication
Red LED status indication
Operating frequency 433MHz
Adjustable detection range approx. 1 to 8 metres
Optional audible pre-alarm output
12Vdc 1A alarm output
12 Vdc 1A door lock output (lock time 5-75 seconds in 5 second increments)
Optional continuous lock untill reset
Normally open hard wired reset input
Normally closed door contact input to prevent alarm if door closed
Fully user programmable
Dimensions 720 x 30 x 20 mm
White durable ABS plastic enclosure
Low battery and AC power loss detection and alert

ACCESSORIES

2555 Central Monitor, **2556** Desktop Care Station, **2404** Plug pack, **2401** 1A Power Supply, **2402** 2.5A Power Supply, **2403** 5A Power Supply, **2515** Infant Transmitter Transmitter, **2528** Caregiver Reset Transmitter, **2519** DoorAlert Tester, **2421** Magnetic Electric Door Lock, **2420** Electric Door Strike, **2642** Caregiver Reset Key, **2434** SmartGuard Keypad, **2474** Curtain PIR, **2452** Magnetic Reed Switch, **2453** Magnetic Reed Switch, **2454** Magnetic Reed Switch, **2455** Magnetic Reed Switch, **2450** Push Button, **2451** Single Gang Wall Plate

cura1.com

cura¹ products are designed to augment well designed care programs and practices, cura¹ does not claim that any of its products are suitable as a substitute, or as a total solution for individuals that require care and constant supervision, and are at risk.