Economy Incontinence Monitor



PART NUMBER: **4020**

FEATURES

Simple operation and maintenance
Works with all Economy Incontinence Pads
Red LED visual alarm indicator
3 x AAA battery operated or optional 6 V external plug pack
3 selectable alarm tones
Can be connected to a nurse call system
Adjustable alarm volume
Front panel reset / self test button
“Low Battery” audible alarm & red LED visual warning
Selectable delay options 0 sec / 1 sec / 2 sec
Comes complete with mounting strap

TECHNICAL SPECIFICATIONS

DC operation using either a 3 x AAA batteries or 6 V plug pack
Dimensions 70 x 105 x 40 mm durable ABS plastic enclosure
Weight 115 g without batteries
3 selectable alarm tones
Alarm mute switch
3 delay options 0 sec / 1 sec / 2 sec
Volt free normally open relay contact alarm output
RJ10 type socket for wired incontinence connection
Low battery detection and indication 3.3 Vdc trigger point

ACCESSORIES

4022 Chair Incontinence Pad, **4021** Bed Incontinence Pad, **2406** Plug Pack, **2643** Nurse Call Cable

cura1.com

cura¹ products are designed to augment well designed care programs and practices, cura¹ does not claim that any of its products are suitable as a substitute, or as a total solution for individuals that require care and constant supervision, and are at risk.