Desktop Care Station



PART NUMBER: 2556

FEATURES

Wireless alarm monitor for use with other cura1 wireless products

Desktop mountable

Output for connection to printer

Indicates other cura1 wireless equipment low battery and fault conditions

Easy installation and simple operation

Low maintenance and long battery life

Fully wireless - no cabling required

Automatic “read-in” programming

High visibility flashing LED light and adjustable audible alarm

Can be connected to a nurse call system

Caregiver key reset option

ACCESSORIES

2615 Wireless Bed Monitor, **2608** Wireless Bed Monitor, **2404** Plug pack, **2401** 1A Power Supply, **2402** 2.5A Power Supply, **2403** 5A Power Supply, **2561** Wireless Indicator Light, **2562** Wireless Bumper, **2552** Door Monitor, **2572** Wrist Band Transmitter, **2573** Wrist Band Transmitter, **2558** Wireless Call Button, **2559** Wireless Reset Button, **2642** Caregiver Reset Key

TECHNICAL SPECIFICATIONS

Automatic “read-in” programming procedure

Uniquely identifies up to 200 - 2615 or 2608 Wireless Bed Monitors (FallAlert System)

Uniquely identifies up to 30 Cordless pads and mats across 25 rooms or areas (FallAlert System)

Uniquely identifies up to 1000 - 2572 Resident Transmitters (DoorAlert System)

Uniquely identifies up to 16 - Door Locations (DoorAlert System)

Uniquely identifies up to 1000 - 2558 Wireless Call Buttons (StaffAlert System)

Uniquely identifies up to 1000 - 2573 Wristband Duress Transmitters (StaffAlert System)

Up to 8 unique area IDs

Dimensions 242 x 168 x 116mm

White durable ABS plastic enclosure with plastic membrane front panel

Low battery and AC power loss detection and alert

9-13.8 Vdc operation (stand by current consumption <100mA)

Rechargeable internal backup batteries

Battery life in AC mains fail 10 hours, in stand-by 2 to 3 years

Two line LCD backlit display

Serial output for printer

Red LED and audible sounder low battery indication

Operating frequency 433MHz

Volt free normally open alarm output

User selectable reset functions

Automatic “out of range” and “interference detection” with alert

cura1.com

PM054

cura1 products are designed to augment well designed care programs and practices, cura1 does not claim that any of its products are suitable as a substitute, or as a total solution for individuals that require care and constant supervision, and are at risk.