DoorAlert Door Monitor



PART NUMBER: **2552**

FEATURES

Automatically detects wandering residents and alerts carers

Fully wireless – no cabling required for easy installation, configuration, operation, expansions and upgrades

Monitor from 1 to 1,000 residents

Individually identifies each resident (when used with LRCS Care Station)

Flashing LED and adjustable audible alarm

Can be connected to a nurse call system and electronic locking devices

Caregiver Reset Key, Smartguard Keypad and Reset Transmitter options

Magnetic door contact input can inhibit alarm activation if the door is closed

Night Mode – To protect a facility at night, any monitored door opened will alert staff / caregivers

TECHNICAL SPECIFICATIONS

9-13.8 Vdc operation (stand by current consumption < 100 mA)

Red LED and adjustable audible sounder alarm indication

Operating frequency 433 MHz

Adjustable detection range approx. 1 to 8 metres

Optional audible pre-alarm output

12 Vdc 1 A alarm output & door lock output

Optional continuous lock output until reset

Normally open hard wired reset input

Normally closed door contact input to prevent alarm if door closed

Dimensions: 720 x 30 x 20 mm, white ABS plastic enclosure

Dry Contact Relay Outputs for easy 3rd party connection

Latching Lock - Doors remain locked while the resident is in the vicinity of the Monitor unless overridden by staff

ACCESSORIES

2404 Plug pack, **2420** Electric Door Strike, **2434** SmartGuard Keypad, **2451** Single Gang Wall Plate, **2572** Wrist Band Transmitter, **2575** Caregiver Reset Transmitter, **2501** LRCS Care Station, **2502** LRCS Zone Repeater, **2577** System Tester, **2642** Caregiver Reset Key, **3500** ActiveCare Console, **3501** ActiveCare Pager

cura1.com

cura¹ products are designed to augment well designed care programs and practices, cura¹ does not claim that any of its products are suitable as a substitute, or as a total solution for individuals that require care and constant supervision, and are at risk.