cura1

SeizureAlert Wireless Remote Alarm & Bed Fall Option



PART NUMBER: **3016**

FEATURES

Works with 3010 SeizureAlert Monitor
Alert carers if person being cared for falls out of bed
Transmits a wireless alarm signal to the remote alarm unit
50m Transmission range
Easy installation & setup
Battery backup
Minimal false alarms
Connects easily with third party alarm devices
Can detect seizure movement and sound
12 Month guaranteed life expectancy for bed pad

ACCESSORIES

3010 SeizureAlert Monitor, **3017** Call Button Option,
2405 Plug Pack, **2404** Plug Pack

TECHNICAL SPECIFICATIONS

Remote Alarm Unit:
Operating frequency: 433.92MHz RX
Typical operating range 50m (dependent on environmental conditions)
Power requirements: regulated 12Vdc plug pack & batteries: 4.5V (3 x C type cells)
Power consumption < 100mA
Adjustable alarm volume and tones
Durable ABS plastic enclosure
Dimensions of housing: 130mm x 95mm x 35mm.
Weight 140g

Bed Monitor:
9 Volt DC operation using either a 9V battery or 9V plug pack.
Power on/off switch.
Dimensions 120 x 77 x 25 mm durable plastic enclosure.
Blue LED alarm indicator light.
Adjustable internal sounder.
3 selectable alarm tones.
Volt free normally open and normally closed alarm output.
RJ11 type socket for bed pad connection with strain relief.
Low battery detection and indication.
Missing AC/DC supply detection and indication

cura1.com

cura¹ products are designed to augment well designed care programs and practices, cura1 does not claim that any of its products are suitable as a substitute, or as a total solution for individuals that require care and constant supervision, and are at risk.