Wireless Call Button with Reset and Pull Cord



PART NUMBER: **2558**

FEATURES

Wireless call button for use with other cura[1] wireless equipment

Integrated reset button

IP65 certified

Easy installation and simple operation

Removable pull cord

Red LED reassurance light when switch activated

Low maintenance and long battery life

Fully wireless - no cabling required

Low battery indication

TECHNICAL SPECIFICATIONS

6 Vdc operation (2 x 3 volt lithium cells CR2477) (supplied, replaceable)

Battery life 1 to 2 years depending on usage

Operating frequency 433 MHz

Fully user programmable using Caregiver Reset Key

Dimensions 85 x 85 x 22 mm

White durable plastic enclosure with plastic membrane front panel

50 m* range when used with other cura[1] wireless products

ACCESSORIES

2544 & **2549** Wireless Multiport Expanders, **2561** Wireless Indicator Light, **2642** Caregiver Reset Key, **2700** Six Channel Cordless Monitor, **3500** ActiveCare Console, **3501** ActiveCare LCD Pager, **3508** LED Pager

cura1.com

cura[1] products are designed to augment well designed care programs and practices, cura1 does not claim that any of its products are suitable as a substitute, or as a total solution for individuals that require care and constant supervision, and are at risk.

* Dependent on environmental conditions