DoorAlert LT Kit



FEATURES

Fast, simple 'plug & play' setup and installation - no specialist installers required

Robust, stable and consistent performance. This unit punches well above its weight, compared to similar products available

Only the monitored person is detected. Alarms can not be caused by pets or other household members

Can be used with an electric door lock to prevent egress

Flexibility; the system can be configured in a variety of ways and expanded to use additional alarm devices

Tamper-proof installation

Transmitter low battery indication

Transmitter can be worn on the wrist, as a pendant or attached to clothing

Escort mode allows a carer to escort a monitored person through a door without activating an alarm

TECHNICAL SPECIFICATIONS

4000 DoorAlert Monitor

- Detection range adjustable from 1 - 4 m
- 12 VDC operation (power consumption: 150 mAH Maximum)
- Red LED and adjustable sounder alarm indication
- Operating Frequency: 125KHz trans. and 2.4GHz rec.
- Optional continuous lock output while wristband is present
- Door Contact & PIR input to inhibit alarm if door closed or no movement detected
- Dimensions of housing: 360 x 70 x 35 mm
- White durable ABS plastic enclosure

4001 Wristband Transmitter

- Battery life:12 months (@10 triggers / day). 10 year storage (sleep mode).
- Lightweight (28 grams)
- Dimensions: 32 (W) x 45 (L) x 12 (H) mm
- Rated IP66 for dust & water protection

ACCESSORIES

2642 Caregiver Reset Key, **4001** DoorAlert LT Resident Wristband Transmitter, **2569** Plastic Wrist Straps, **2589** White Buckle Wrist Strap, **4002** Wireless DoorAlert LT Reset Button, **2404** Plug Pack 12 Vdc, **2567** Lanyard with Safety Break Clip

cura1.com

cura¹ products are designed to augment well designed care programs and practices, cura¹ does not claim that any of its products are suitable as a substitute, or as a total solution for individuals that require care and constant supervision, and are at risk.