ActiveCare LED Pager



PART NUMBER: **3508**

FEATURES

Can be programmed to monitor up to 3 wireless devices

Vibration and tone selection for hard of hearing

Auto-reset when paired with a 2719 transmitter

Direct signalling from wireless devices for use in home care environments

Easily cleanable buttons for a hospital setting

TECHNICAL SPECIFICATIONS

Operating frequency: 433.92 MHz

Power requirements: 2 x AA batteries (included)

Dimensions (L x W x D): 83 x 55 x 26 mm

Housing material: durable ABS plastic

Net Weight: 65 g (without batteries)

Operating temp.: 5°C to 40°C

Rel. humidity: < 90%

ACCESSORIES

All **Cordless** Pads & Mats (using a **2719 or 2720** transmitter), **2721** iBeam, **2588** PET, **2558** Wireless Call Button, **2595** Wristband Alarm Transmitter, **2599** Wireless SOS Call Button, **3502** Wireless Handset, **3503** Wireless Magnetic Door Switch, **3504** ActiveCare Bracket, **3506** Soft Cover

cura1.com

cura¹ products are designed to augment well designed care programs and practices, cura¹ does not claim that any of its products are suitable as a substitute, or as a total solution for individuals that require care and constant supervision, and are at risk.