Wristband Transmitter



PART NUMBER: **2572**

FEATURES

For use with cura1 DoorAlert Wandering Resident System

Lightweight and small in size

Low cost and low maintenance

Guaranteed 12 months continuous operation

Can be activated by installers

Transmits low battery condition to Central Monitor

TECHNICAL SPECIFICATIONS

Operating frequency 433 MHz

Lithium battery (600 mAh) allowing one year life, 10 year storage (in sleep mode)

400 mS periodic digital transmissions

Unique identity coding

Programming functions password protected

Can be switched on/off using caregiver reset key

Code and function programmable using caregiver reset key

Used with disposable plastic wrist straps

Lightweight (4 grams) and small watch-size, 36 mm diameter, 11 mm height

Dust & water resistent to IP67

ACCESSORIES

2552 DoorAlert Strip Monitor, **2569** Plastic Wrist Straps, **2577** System Tester, **2642** Caregiver Reset Key

cura1.com

cura1 products are designed to augment well designed care programs and practices, cura1 does not claim that any of its products are suitable as a substitute, or as a total solution for individuals that require care and constant supervision, and are at risk.